UL Listed Hurricane-Resistant HC8800 Rim Exit Device

80 Series





ASSA ABLOY


HC8800 Series Rim Exit Device



HC8800, 12-HC8800 Series Rim Exit Device

- Chassis: ductile iron
- Requires 2 chassis shims and 2 end bracket shims included with the exit device
- Additional information on HC980 Mullions available in Mullion Section of this catalog

Single Door



Features

- Designed for standard width stile applications on metal doors.
 For doors 1-3/4" (44mm) thick.
- Devices are ANSI A156.3
- UL Fire and Panic listed


Rails are available in 4 sizes, use door width to determine size needed. Rails will be factory cut to size, if door width is supplied

- E Rail for 24" to 32" door widths, No cutting required for 32" door
- F Rail for 33" to 36" door widths, No cutting required for 36" door
- J Rail for 37" to 42" door widths, No cutting required for 42" door
- G Rail for 43" to 48" door widths, No cutting required for 48" door **Note:** For additional information on 8800 Series, see page 6


649 Strike

- Supplied standard for panic & fire rated openings
- Surface applied
- Black nylon coated





Double Door HC-8800 with HC-980 Mullion



UL Listed Hurricane-Resistant HC8800 Functions & Trims



Options for

Available Finishes

BHMA Finishes

605

606

611

612

613

613E

614

618

619

624

625

626 629

630

SARGENT Finishes

03

04

09

10

10B

10BE

10BL

14

15

20D

26

26D

32

80 Series

How to order: Options 12	Series HC88	Function 13	n Rail Lgth F	Trim ETL	Hand RHR	Outside Finish 15	Inside Finish 32D	Door Width 36"	НС8800		
700 Series ET Trim Exits with ET Trim, specify	_ Fund	SARGENT ANSI Function Function Numbers Numbers		Description & Cylinder Info (1-3/4" Door)				ANSI Type 1 HC8800 Panic & Fire	Mechanical Options: 12- 16- 19- 31-		
lever design after the ET designation (e.g., ETL)	0	14	03			Night Latch Key Retracts Latch 4 Cylinder Supplied		HC8804 x ET_	36- 37- 43- 54- 55- 56- 56-HK- 57- 58- 76- 85- 86-		
9	0	16	09		Trim rel	ks Trim, Trim retracts latc ocks when key is removed 11 Cylinder Supplied	n/	HC8806 x ET_			
	1	0	01		No outsi	de operation (No Cylinder)	HC8810			
Lever Designs for ET Controls A, B, E, F, J, L, P, W	- 1	0	02		No outside operation (No Cylinder) ET Control is used as Pull Only)	HC8810 x ET_	87- BT- CPC- LD-		
Also available with Coastal Series & Studio Collection Levers ET Designation with Suffix (Used to order ET without device) HC-8800 Series: 704, 706-8, 710,	1	#41 Cyllidei Supplied						HC8813 x ET_	PL- SG- TB- TL- Cylinder Options: 10- 10-21- 10UL- 10-63- 11- 11-60- 11-63- 11-64- 11-70-7P- 11-72-7P- 11-73-7P-		
	- 1							HC8815 x ET_			
713-8, 715-8, 740, 743-8, 744, 746-8, 773-8, 774-8, 775-8 & 776-8	4	Freewheeling Trim - No outside operation HC (No Cylinder) Dummy Trim					HC8840 x ET_				
Freewheeling Trim The lever rotates when the door is locked preventing excessive force fror being applied to the horizontal lever	— m 4	Freewheeling Trim - 43 08 Key Outside Unlocks/locks Trim HC8843 : #41 Cylinder Supplied						HC8843 x ET_			
Electrified ET Trim	4	4	03 Freewheeling Trim - Key Retracts Latch HC8					HC8844 x ET_	11-65-73-7P- 21- 22- 51-		
Voltage must be specified for the following functions: 73, 74, 75 and 70 Specify: 12VDC or 24VDC	5. 4	6	09		Key unloc Trim rel	reewheeling Trim - ks Trim, Trim retracts latcl ocks when key is removed 11 Cylinder Supplied	n/	HC8846 x ET_	52- 60- 63- 64- 70- 72-		
any is promoted	75	++			Pov	rified ET Trim - Fail Safe ver Off, Unlocks Lever, Key Retracts Latch 14 Cylinder Supplied		HC8875 x ET_	73- 73- 65-73- 65-73-7P- 73-7P- 81-		
	76	5**			Po	fied ET Trim - Fail Secure wer Off, Locks Lever, Key Retracts Latch 14 Cylinder Supplied		HC8876 x ET_	82- F1-82- 83- F1-83- 84-		
Solution of Salgent (Mailting Company) is promoted.	in 32 or 14/32 or ++ 75 Fu	Note: Exit devices are available in all standard finishes, except 14, 15, 26 & 26D. With these finishes, exit devices are supplied in 32 or 32D to match accordingly. 26 or 26D is automatically supplied when 32 or 32D is specified. For nickel finishes, specify 14/32 or 15/32D to receive nickel finished trims and stainless exit devices. ++ 75 Function without cylinder is available as a 73 Function ** 76 Function without cylinder is available as a 74 Function									

Trim Designations

- Use three letter designations (Ex "PTB") when ordering the Exit Device with Trim

Use the six digit designation (Ex "814-MSL") when
ordering trim without an Exit Device, always specify finish

uring ie exp	Dull Coction				ordering trim without an Exit Device, always specify finish					
-2014 rhole c	Pull Section SARGENT Function Numbers	ANSI Function Numbers	Function Description & Cylinder		ĵ		f		HC800 Panic & Fire	
	04	03	Night Latch-Key Retracts Latch #34 Cylinder Supplied	814-FSL*	814-FSW*	814-MSL*	814-PSB*	814-STS	HC8804 x Trim Designation	
U &	10	02	No O/S Operation or Cylinder (Pull Only)	810-FLL	810-FLW	810-MAL	810-PTB	810-STS	HC8810 x Trim Designation	

* FSL, FSW, MSL and PSB trims are used with (HC-& 12-) 8888 and 8804 only and are the same as FLL, FLW, MAL and PTB pulls except for cylinder hole located 3/8* (9mm) lower Note: FLW & FSW trims are not available in 32(629) or 32D(630)

90641:P6/1/14

Series